



Spektrum Surface Receivers

ITEM	DESCRIPTION	AVAILABILITY	CHANNEL OUTPUTS	SMART COMPATIBLE	PROGRAMMABLE AVC	USER UPDATEABLE	WATER RESISTANT	BIND METHOD	MODULATION	XBUS PORT	INTEGRATED TELEMETRY	TELEMETRY RANGE	FAILSAFE TYPE	DIMENSIONS	WEIGHT	ANTENNA LENGTH	INPUT VOLTAGE	SUGGESTED APPLICATION									
SPMXSE1040RX	Firma 40 Amp Smart ESC with 4CH DSMR		4	Yes	No	Yes	Reliacoated	Button	DSMR/DSM2	No	Yes	Drive-By	Smart-Safe and Hold Last	1.3 in (33.5mm)x 0.81 in (20.5mm)	2.4oz (68g)	1.2 in (31mm)	6-10.8V	x	x	x							
SPMSR6100AT	SR6100AT 6 Channel AVC/Telemetry Surface Receiver		6	Yes	Yes	Yes	Reliacoated	Button	DSMR/DSM2	Yes	Yes	Full Range	Smart-Safe and Hold Last	0.94" (23.9mm)x 0.59" (15.1mm)	0.35oz (10g)	4.7" (120mm)	3.5 - 9.6V			x	x	x	x		x		
SPMSR2100	SR2100 3CH Micro DSMR Racing Rx Antennaless		3	No	No	Yes	None	Button	DSMR/DSM2	No	No	NA	Smart-Safe and Hold Last	1.0 in (25.5 mm)x1.0 in (25 mm)	0.2 oz (5.5g)	N/A	3.5-9.6V	x		x	x	x					
SPMSR515	SR515 DSMR 5 CH Receiver		5	Yes	No	Yes	None	Button	DSMR/DSM2	No	Yes	Drive-By	Smart-Safe and Hold Last or Gas mode	0.84 in (21.4 mm)x 0.53 in (13.6 mm)	0.21 oz (6.0 g)	4.72 in (120 mm)	3.5-9.6 V	x	x	x	x	x	x	x	x	x	x
SPMSR315	SR315 DSMR 3 CH Receiver		3	Yes	No	Yes	None	Button	DSMR/DSM2 /SLT	No	Yes	Drive-By	Smart-Safe and Hold Last or Gas mode	0.84 in (21.4 mm)x 0.53 in (13.6 mm)	0.21 oz (6.0 g)	3.54 in (90 mm)	3.5-9.6 V	x	x	x	x	x	x	x	x	x	
SPMSR215	SR215 DSMR 2 CH Receiver		2	Yes	No	Yes	None	Button	DSMR/DSM2	No	Yes	Drive-By	Smart-Safe and Hold Last or Gas mode	0.84 in (21.4 mm)x 0.53 in (13.6 mm)	0.21 oz (6.0 g)	3.54 in (90 mm)	3.5-9.6 V	x	x	x	x	x	x	x	x	x	
SPMSRX300	SRX300 3Ch 2.4 GHz FHSS RX		3	No	No	No	None	Plug	FHSS	No	No	NA	Smart-Safe and Hold Last	N/A	N/A	N/A	N/A	x	x	x	x	x					
SPMMR4000	MR4000 DSMR 4 Ch Marine Receiver		4	No	No	No	Potted	Plug	DSMR/DSM2	No	No	NA	Smart-Safe and Hold Last	0.9 in (22.1 mm)x0.5 in (12.2 mm)	0.6 oz (17g)	455mm	3.5-9.6V		x							x	
SPMMRX200	MRX200 Marine 2-Ch FHSS Receiver		2	No	No	No	Potted	Plug	FHSS	No	No	NA	Smart-Safe and Hold Last	N/A	N/A	N/A	N/A		x								x
SPMSRS4200 - SRS4220	4 CH AVC Surface Receivers	Discontinued	4	No	Yes	No	Reliacoated	Plug	DSMR/DSM2	No	No	NA	Smart-Safe and Hold Last	N/A	N/A	N/A	N/A				x	x	x			x	
SPMSRS6000	SRS6000 6 Channel AVC Surface Receiver	Discontinued	6	No	Yes	No	Reliacoated	Plug	DSMR/DSM2	No	No	NA	Smart-Safe and Hold Last	0.96 in (24.4mm)x0.51 in (13mm)	0.39 oz (10.9g)	210mm	3.5-9.6V				x	x	x			x	
SPMSR410 / SPMSR415	SR410 DSMR 4CH Receiver	Discontinued	4	No	No	No	None	Plug	DSMR/DSM2	No	No	NA	Smart-Safe and Hold Last	N/A	N/A	210mm	N/A			x	x	x	x	x		x	
SPMSR2000/SPMSR2010	SPMSR2010 DSMR Micro Racing Receiver	Discontinued	3	No	No	No	None	Plug	DSMR/DSM2	No	No	NA	Smart-Safe and Hold Last	0.70 in (17.6mm)x 0.50 in (13.6mm)	2.0 oz (5.5g)	93mm	N/A	x		x	x	x					
SPMSR4000T	SR4000T 4 Ch DSMR 4CH Slim Surface Rec w/Telemetry	Discontinued	4	No	No	Yes	Reliacoated	Button or Plug	DSMR/DSM2	Yes	Yes	Full Range	Smart-Safe and Hold Last	1.1 in (27.7mm)x 0.6 in (15.7mm)	0.3 oz (9.2g)	210mm	3.5-9.6V		x	x	x	x	x	x	x	x	
SPMSR6000T	SR6000T 6 CH Telemetry Surface Receiver	Discontinued	6	No	No	Yes	Reliacoated	Button or Plug	DSMR/DSM2	Yes	Yes	Full Range	Smart-Safe and Hold Last	1.1 in (27.7mm)x 0.6 in (15.7mm)	0.3 oz (9.2g)	210mm	3.5-9.6V		x	x	x	x	x	x	x	x	
SPMSR310	SR310 3CH DSMR Receiver	Discontinued	3	No	No	No	None	Plug	DSMR/DSM2	No	No	NA	Smart-Safe and Hold Last	N/A	N/A	210mm	3.5-9.6V		x	x	x	x					
SPMSR300	SPMSR300 3CH DSM Receiver	Discontinued	3	No	No	No	None	Plug	DSM	No	No	NA	Smart-Safe and Hold Last	N/A	N/A	N/A	N/A			x	x	x					
SPMSR3100	SR3100 DSM2 3-Ch Receiver	Discontinued	3	No	No	No	None	Plug	DSM2/DSM	No	No	NA	Smart-Safe and Hold Last	N/A	N/A	N/A	N/A			x	x	x	x	x			
SPMSR300WP	SR300WP 3-Ch DSM Sport Receiver Waterproof	Discontinued	3	No	No	No	Potted	Plug	DSM	No	No	NA	Smart-Safe and Hold Last	N/A	N/A	N/A	N/A			x							x
SPMSR210	SR210 DSMR 2 Ch Sport Rec	Discontinued	2	No	No	No	None	Plug	DSMR/DSM2	No	No	NA	Smart-Safe and Hold Last	0.9 in (23.6mm)x0.6 in (14.3mm)	0.3 oz (8.8g)	210mm	3.5-9.6V		x	x	x	x					
SPMSR200	SR200 2-channel DSM Sport Receiver	Discontinued	2	No	No	No	None	Plug	DSM	No	No	NA	Smart-Safe and Hold Last	N/A	N/A	93mm	N/A			x	x	x	x				